

PingThemAll Emails & Reports

September 1, 2022

PingThemAll Pro can send two different kinds of e-mails: Device Status Changes and Daily Summaries

Device Status Change E-mails:

To receive a device status change e-mail, three things must be in place:

1. The config.ini file SCEM option must be set to SCEM=1
2. The config.ini ADDR option must be set to a valid e-mail address, such as [ADDR=joe@abc.org](mailto:joe@abc.org)
3. The pingthese.txt file must have email specified for that device

When a device status changes, this information will be stored by the PingThemAll (PTA) engine. After PTA is finished that cycle, an e-mail will be generated with all status changes and sent to the specified e-mail address.

The e-mail will come from pta@pingthemall.com, formatted like this example:

```
From: pta@pingthemall.com
To: joe@abc.org (your e-mail address)
Subject: ABC Device Status Changes 7/16/2022, 1:53:47 PM

[Sat 07/16/2022][13:20:43.72] Switch HQ Third Floor #1 [10.10.40.60] Ping Failed.
-----
[Sat 07/16/2022][13:20:51.43] Switch HQ Third Floor #2 [10.10.40.61] Ping Failed.
-----
[Sat 07/16/2022][13:22:22.17] Previous ping failure cleared: Copier [10.10.101.7] is now responding.
-----
End of ABC device status changes alert. PingThemAll Pro version 2.0.1.4
```

Daily Summary E-mails:

To receive a daily summary e-mail, two things must be in place:

1. The config.ini file SUMM option must be set to SUMM=1
2. The config.ini ADDR option must be set to a valid e-mail address, such as [ADDR=joe@abc.org](mailto:joe@abc.org)

Whenever a new day occurs, or PingThemAll is stopped and restarted, a Daily Summary e-mail will be sent. This summary will be a collection of all device status changes. The e-mail will also report the total number of devices you are monitoring. If no devices have changed status in the last 24 hours, a summary e-mail will still be sent that states this.